


## Switchmode/ High Frequency Rod Core Inductors

## F I R C H - 3

## **Description:**

Triad high current rod core inductors provide cost effective energy storage. By conditioning the output signal, the inductor smoothes out the current waveform to provide a more stable current. These low cost inductors are designed to be compatible with automated P.C.B. installation.




## **Outline Dimensions:**

A. Dimensions: As figure show Unit: In inch

B. PIN DIM. : As figure show C. WT Lbs. : 0.03 Lbs.

Type No.	+/- 15%	DC Rated	Max. DC Resistance	Lead
	Inductance uH	Current	(mOhms)	Diameter
FRICH-3	3.60	8.10A	9.95	0.040"

Inductance at 20KHz to 200KHz Rated current 40C temperature rise. Operating Temperature: -40°C to +85°C



**RoHS Compliance:** As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.

\*Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics website for the most current version. For soldering and washing information please see http://www.triadmagnetics.com/faq.html

web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757 460 Harley Knox Blvd. Perris, California 92571

Publish Date: June 5, 2019